

タッチパネルコントローラ別OS対応表

S1240305C

2024年3月

USB I/F	DUSx000	DUSx200	TSC-52	TSC-54/55	MTR20x0
WindowsXP~11*	DMC Driver OS Driver	DMC Driver OS Driver	DMC Driver OS Driver	DMC Driver	DMC Driver OS Driver
Linux & Android	Kernel 3.5以降: OS Driver Kernel 2.6.35~3.4: DMC Driver	Kernel 3.5以降: OS Driver Kernel 2.6.35~3.4: DMC Driver	Kernel 3.5以降: OS Driver Kernel 2.6.35~3.4: DMC Driver	Kernel 3.5以降: OS Driver Kernel 2.6.35~3.4: DMC Driver	Kernel 3.5以降: OS Driver Kernel 2.6.35~3.4: DMC Driver
QNX	QNX 7.1以降 : OS Driver (未確認)	QNX 7.1以降: OS Driver (未確認)	QNX 7.1以降 : OS Driver (未確認)	QNX4 Product Suite 2010 : OS Driver (未確認)	QNX 7.1以降 : OS Driver (未確認)

UART又はRS-232C I/F	DUSx000	DUSx200	TSC-52	TSC-54/55	MTR20x0
	UART	UART	RS232C	RS232C	UART
WindowsXP~11*	DMC Driver	DMC Driver	DMC Driver	DMC Driver	DMC Driver
Linux	kernel 3.14 : DMC Driver	kernel 3.14 : DMC Driver	-	Kernel 3.2以降 : OS Driver Kernel 2.4.22~3.9.5 : DMC Driver	kernel 3.14 : DMC Driver
Android	kernel 3.14 : DMC Driver	kernel 3.14 : DMC Driver	-	-	kernel 3.14 : DMC Driver

I2C I/F	DUSx200	
	Original Protocol	HID over I2C
WindowsXP~11*	-	Windows10 以降 : OS Driver
Linux & Android	Kernel 3.8.13 & 4.14.94 : DMC Driver	kernel 3.8以降 : OS Driver

*WindowsXPにおいては、シングルタッチのみ可能。

本資料は参考用としてのみご利用ください。

ドライバの対応可否はOS構成に依存するため、ご採用際には必ず実環境でテストを実施してください。

DMC Driver = DMCが提供するドライバで動作可能

OS Driver = OS搭載のドライバで動作可能

Linux又はAndroid用DMC Driverをご要望の場合は、弊社までお問い合わせください。

