タッチパネルコントローラ別OS対応表

S1240305E
2025年4月

USB I/F	DUSx000	DUSx200	TSC-52	TSC-54/55	MTR20x0
WindowsXP～11*	DMC Driver OS Driver	DMC Driver OS Driver	DMC Driver OS Driver	DMC Driver	DMC Driver OS Driver
Linux & Android	Kernel 3.5以降: OS Driver Kernel 2.6.35～3.4: DMC Driver	Kernel 3.5以降: OS Driver Kernel 2.6.35～3.4: DMC Driver	Kernel 3.5以降: OS Driver Kernel 2.6.35～3.4: DMC Driver	Kernel 3.5以降: OS Driver Kernel 2.6.35～3.4: DMC Driver	Kernel 3.5以降: OS Driver Kernel 2.6.35～3.4: DMC Driver
QNX	QNX 7.1以降：OS Driver (未確認)	QNX 7.1以降: OS Driver (未確認)	QNX 7.1以降：OS Driver (未確認)	QNX4 Product Suite 2010：OS Driver (未確認)	QNX 7.1以降：OS Driver (未確認)

UART又はRS-232C I/F	DUSx000	DUSx200	TSC-52	TSC-54/55	MTR20x0
	UART	UART	RS232C	RS232C	UART
WindowsXP～11*	DMC Driver	DMC Driver	DMC Driver	DMC Driver	DMC Driver
Linux	kernel 3.14：DMC Driver	kernel 3.14：DMC Driver	-	Kernel 3.2以降：OS Driver Kernel 2.4.22～3.9.5：DMC Driver	kernel 3.14：DMC Driver
Android	kernel 3.14：DMC Driver	kernel 3.14：DMC Driver	-	-	kernel 3.14：DMC Driver

I2C I/F	DUSx200
Protocol	Original Protocol
WindowsXP～11*	-
Linux & Android	Kernel 3.8.13 & 4.14.94：DMC Driver

*WindowsXPにおいては、シングルタッチのみ可能。

DMC Driver = DMCが提供するドライバで動作可能
OS Driver = OS搭載のドライバで動作可能

Linux又はAndroid用DMC Driverをご要望の場合は、弊社までお問い合わせください。

本資料は参考用としてのみご利用ください。
ドライバの対応可否はOS構成に依存するため、ご採用の際には必ず実環境でテストを実施してください。

Microsoft® Windows®は米国Microsoft Corporationの米国およびその他の国における登録商標です。